

MFJ 945E

MOBILE TUNER 1.8-50 MHZ, 300 W PEP | WITH MINI CROSS METER



MFJ-945E mobile Tuner now covers 6-meter band and has antenna bypass Switch!

Efficient airwound inductor gives you lower losses and more Watts out. 1000 Volt capacitors. Covers 1.8 to 60 MHz. Convenient placement of controls makes tuning fast and easy while in motion. Antenna switch lets you bypass tuner and still use the SWR/Wattmeter.

Back panel has SO-239 connectors for transmitter and coax and a wing nut post for your ground.

The Cross-Needle meter shows SWR, forward and reflected power. It reads forward/reflected power in 300/60 and 30/6 Watt ranges. ON/OFF lamp switch. Requires 12 volts for lamp.

Specifications

Frequency range : 1,8 - 54 MHz

Antenna : 1x coaxline; with external balun also for balanced line

Bypass : Yes

Meter : Cross-Needle meter for SWR, forward and reflected power in 300/60 and 30/6 Watt ranges. Incl. meter light (12 VDC)

Power : max. 300 W PEP

Dimensions : W 203 x D 152 x H 50 mm



Article id: **MFJ 945E**

Price: **€ 179,00**

ex VAT € 147,93

Classic International B.V.

Zuidhoven 9 G

6042 PB Roermond

The Netherlands

info@classicinternational.eu

<https://www.classicinternational.eu>

Copyright © 2021 Classic International B.V.

Printing errors reserved

Date: 17-01-2021