

# MIRAGE B-34G

2 M. LINEAR AMP. | PREAMP  
OUTPUT 35 W



Mirage B-34G - 2 Meter Power Amplifier including Low Noise Preamp to boost the power of your FM handheld radio.

First class stripline technique provides excellent RF performance. The B-34 is protected against reversed polarity.

#### Power curve

Input 0,25 W : Output 8 W  
Input 0,5 W : Output 12 W  
Input 1 W : Output 18 W  
Input 2 W : Output 30 W  
Input 3 W : Output 33 W  
Input 4 W : Output 35 W

#### Specifications

Frequency : 144-148 MHz  
Modes : FM only  
RX Low Noise Preamp : yes  
Consumption : 4 A  
Supply voltage : 13,8 VDC  
Connections : SO 239  
Dimensions : W 133 x D 110 x H 45 mm

Article id:	<b>MIRAGE B-34G</b>	
Price:	<b>€ 225,00</b>	<b>ex VAT € 185,95</b>