

# MFJ 836

## ALL-IN-ONE RF AMMETER/SWR/WATTMETER



The MFJ-836 is an all-in-one RF Ammeter/SWR/Wattmeter! You can quickly determine feedpoint impedance and monitor your antenna system for detrimental changes under power.

Read RF current in three calibrated ranges -- 0.3, 1, 3 Amperes. A large 3-inch lighted easy-to-read Cross-Needle meter lets you read SWR, forward (300/3000W) and reflected power (60/600W) simultaneously.

MFJs exclusive TrueActive™ circuit gives you true peak or average power readings.

### Specifications

#### SWR/Power meter

Frequency range : 1 - 30 MHz  
Antennas : Coaxial feedline  
Power : 300/3000 W || true peak or average power reading  
Meters : SWR/power Cross-Needle Meter  
Connectors : SO 239

#### Ammeter

Frequency range : 1 - 30 MHz  
Antennas : Coaxial feedline  
RF Current : 300mA, 1A, 3A  
Meter : Ammeter  
Meter range : 0/100  
Connectors : SO 239

#### General

Dimensions : W15,3 x H9 x D11,5 cm  
Power supply : 9V battery, 12VDC or 220VAC with adapter (not included)



Article id: **MFJ 836**

Price: **€ 185,00**

ex VAT € 152,89