

CUSHCRAFT A50-3S

BEAM 3 EL. | 50-54 MHZ



The Cushcraft A50-3S computer-aided modeling and test range techniques were used by Cushcraft engineers to further optimize the performance of the popular 6 meter yagi's. This process means more gain and cleaner patterns with excellent front-to-back ratios.

Cushcraft antennas are designed to survive 80 MPH winds. The matching system is the proven Cushcraft Reddi-Match for 50 Ohm no balun and SO-239 connector.

Specifications

Frequency range : 50-54 MHz
Number of Elements : 3
Forward Gain : 5,85 dBd (8,0 dBi)
Front-To-Back Ratio : 20 dBd
Boom Length : 1,80 m
Longest Element : 3,00 m
Turning Radius : 1,80 m.
Surface Area : 3,0 m²
Windload : 0,17 m²
Accepts Mast : 32-50 mm
Matching Sytem : Reddi (Gamma)-Match, SO 239 (PL-female) connector
Max. power : 1000 W PEP
Net Weight : 3,2 kg

Include - all stainless steel hardware and a 2 piece boom - ideal for DXpeditions!

Article id: **CUSHCRAFT A50-3S**

Price: **€ 195,00** ex VAT € 161,16