

KL 405

HF TRANSISTOR AMPLIFIER

OUTPUT APPROX. 200 W



The RM KL-405 is the successor of the KL-400 transistor amplifier. With electronic antenna switch (RF VOX). This new model has an improved bias regulation and therefore more suitable for SSB.

Specifications

Frequency range : 25-30 MHz
Input : 1-10 W AM/FM | 2-20 W SSB
Output : 200 W AM/FM - 400 W PEP SSB | 6-position output power
Pre-amplifier : yes, 26 dB | To be used also when the amplifier is not working
Power supply : 12-14 VDC
Current : 14-22 A
On/Off switch : yes
Dimensions : W 170 x D 210 x H 62 mm
Weight : 980 gr.

The KL-405 Amplifier is supplied without power cable. Has to be ordered additionally. Max. length 3 m; min. diameter 4,0 mm².



Article id:	KL 405	
Price:	€ 245,00	ex VAT € 202,48