

# AV-CN600/RX-600

SWR/POWER CROSS NEEDLE METER | 1,8-160 MHz



The AV-CN600 is a SWR/Power Meter for HF, VHF and UHF.

## Specifications

Frequency range : 1,8 - 200 MHz (S1) + 140 - 525 MHz (S2)

Type meter : cross needle

Ranges : 30/300/3000 W | Peak and average power

Continuous power rating : CW/SSB 1,2-200 MHz = 300 W | 140-525 MHz = 300 W

Max. power handling : 3 kW - 15 sec. | 2 kW - 30 sec. | 1 kW - 60 sec.

Min. power input : 0,5 W

Precision : 30 W range  $\pm 5\%$  | 300 W range  $\pm 5\%$  | 600 W range  $\pm 7,5\%$  | 3 kW range  $\pm 7,5\%$

Impedance : 50 Ohm

Connectors : 4 x SO 239 (PL female) 2 for transceiver and 2 for antenna

Dimensions : W 150 x D 100 x H 65 mm

Weight : 630 g



Article id: AV-CN600/RX-600

Price: € 105,00

ex VAT € 86,78